Installing the full print driver in MacOS 10.13, 10.14, 10.15, MacOS 11 Big Sur, MacOS 12 Monterey

Newer versions of MacOS add printers using the Apple AirPrint driver by default. This limits the available media settings, and removes all advanced print settings. If you are missing our recommended media settings in your print driver, you will need to delete the AirPrint version and add your printer again using the printer driver supplied by manufacturer. Here are the instructions to reinstall your printer using the full print driver.

First, download and install the driver for your printer from the manufacturers' web site. Next, delete and reinstall your printer in System Preferences:

1.Select System Preferences



2.Select Printers & Scanners

File Nev Ope		0500					
General	Desktop & Screen Saver	Dock	Control	& Region	& Privacy	Spotlight	Notification
	Θ						
Displays	Energy Saver	Keyboard	Mouse	Trackpad	Printers & Scanners	Sound	Startup Disk
	@			*			
iCloud	Internet Accounts	App Store	Network	Bluetooth	Extensions	Sharing	
11				٩			
Users & Groups	Parental Controls	Siri	Date & Time	Time Machine	Accessibility		
logi							





3. Choose your printer from the list. In the large window the KIND: will indicate if it is using the AirPrint driver

AirPrinter

+ -

Canon PRO-1000 Ink low Canon PRO-1000 serie Idle, Last Used

Example- Kind: Canon PRO-1000 series AirPrint

Status: Idle

Default printer: Last Printer Used

Default paper size: US Letter

Share this printer on the network Sharing Preferences...

NOT AirPrinter

+ -

0

• ?

Idle
 Canon PRO-1000
 Ink Iow
 Canon PRO-1000 serie
 Idle, Last Used

Example- Kind: Canon PRO-1000 series *Note the only difference is that it is missing the word AirPrint

Status: Ink low

Share this printer on the network

Default printer: Last Printer Used

Default paper size: US Letter

Sharing Preferences...

٢

٥ (?)

4. Delete the AirPrint Printer

With the AirPrint printer selected, click the minus (-) button below the printer list and select 'Delete Printer'



5.Add your printer using the manufacturer driver by selecting the "+" located in the lower left corner under the list of printers. Select "Add Printer or Scanner"

$\bullet \bullet \bullet \checkmark $	Printers & Scanners Q. Search		Printers & Scanners Q. Search
C458 * Ide, Last Used Canon GP-4000 * Ide Canon IP6720 * Office Canon IP6450 * Office Canon IP6-10 * Ide Canon PRO-10	Canon PRO-200 Open Print Quees Options & Supplies Location: Kimi: Canon PRO-200 saries Estati: Ide	C458 16e, Lat Used 10e, Cart Used 10e, Carton DP-4000 10e, Carton DP220 10e, Carton DP220 10e, Carton DP220 10e, Carton DP250 10e, Carton DP2-10 10e, Carton	Canon PRO-200 Open Print Queue Options & Supples Location: Kind: Canon PRO-200 series Estua: ide
Idie Canon PRO-200 Idie Canon PRO-2100 Idie Canon PRO-2100 Idie	Share this printer on the network Sharing Preferences_	Canon PRO-2100	Share this printer on the network Sharing Preferences.
Click here to add a printer, fax or	Default printer: Last Printer Used	Nearby Printers Canon PRO-1000 series EPSON SC-P600 Series EPSON SC-P600 Series	Default printer: Last Printer Used



6.Select your printer from the list



7.With your printer selected, click on the "Use" menu at the bottom of the window. Select your printer model to use the full driver (without AirPrint). Example: Canon PRO-1000 series.

	Printers & Scanners Q Search		
C458	Canon PRO-200		
Capon GP-4000		Add	
Idle	Open Print Queue		Q Search
Canon iP8720	Ontions & Sumplies	Default ID Windows	Search
• Idle	Options & Supplies	Deraut in Windows	odaron
Canon iPF6450			
• Offline	Location:	Name	∧ Kind
Canon PRO-10	Kinds Capon BBO-200 series	Canon GP-4000	Bonjour
Canada DDO 100	kind. Califor PRO-200 series	Canon PRO-1000 series	Bonjour
a Idle	Status: Idle	Canon PRO-200 series	Bonjour
Capon PRO-200		Canon PRO-2100	Bonjour
S • Idle		Canon PRO-300 series	Bonjour
Canon PRO-2100	Share this printer on the network Sharing Preferences	EFI Fiery ES IC-416 PS Color Server 1.1US(33:D1:0D)	Bonjour
Idle		EPSON ET-8500 Series	USB Multifunction
+ -		EPSON SC-P400 Series	Bonjour
		EPSON SC-P400 Series (IP)	EPSON TCPIP
	Default printer: Last Printer Used	EPSON SC-P600 Series	Bonjour
		EPSON SC-P600 Series (IP)	EPSON TCPIP
	Default paper size: US Letter 0 ?	EPSON SC-P800 Series	Bonjour
		EPSON XP-15000 Series	Boniour
Althe alka		EPSON XP-15000 Series (IP)	EPSON TCPIP
A STATISTICS AND A STATISTICS		EpsonStylusPro3880-1F5277	Bonjour
		EpsonStylusPro3880-1F5277 (IP)	EPSON TCPIP
and the second second		OKI-B512-5EA549	Bonjour
and the second second	and the second se	SC-P5000Series-FCC1F9	Bonjour
		SC-P6000Series-FCCTF9 (IP)	EPSON TCPIP
	A Massal		
and the second second		Name: Canon PRO-1000 series	
		Location:	
		Looditori	
	A DE FORMENTAL	Use ✓ Secure AirPrint	
The start market with the	A Standard Contraction of the second second second	AirPrint	
ALL ALL AND A DATA REPORT OF A DATA AND A DATA			
	TY AN ALCOUNT AND A CONTRACT OF A CONTRACT OF	Canon PRO-1000 series	



8.Select "Add" in the lower right corner. You can double-check the process was successful by checking 'Kind' in the main window. (it will not list 'AirPrint' after the printer name)

	Drintors & Coopport		Add
	Plinters & Scaliners	9 6 -	
C458		Default IP Windows	Search
Idle, Last Used	Canon PRO-200		
Canon GP-4000	Open Print Queue	Name Setting up 'Ca	non PRO-1000 series'
Capon iP9720		Canon GP S	
s Idle	Options & Supplies	Canon PR(
Canon iPF6450		Canon PRt Setting up the de	evice
• Offline	Lagation	Canon PRC	
Canon PRO-10	Location:	Canon PR	Cancel
• Idle	Kind: Canon PRO-200 series	EFI Fiery E	
Canon PRO-100	Status: Idle	EPSON ET-8500 Series	USB Multifunction
Capon BBO-200		EPSON SC-P400 Series	Bonjour
S e Idie		EPSON SC-P400 Series (IP)	EPSON TOPP
Canon PRO-2100	Share this printer on the network Sharing Preferences	EPSON SC-P600 Series (IP)	EPSON TCPIP
• Idle		EPSON SC-P800 Series	Bonjour
+ -		EPSON SC-P800 Series (IP)	EPSON TCPIP
		EPSON XP-15000 Series	Bonjour
	Default printer: Last Printer Used 0	EPSON XP-15000 Series (IP)	EPSON TCPIP
		EpsonStylusPro3880-1F5277 (IP)	EPSON TCPIP
	Default paper size: US Letter 🗘 🕐	OKI-B512-5EA549	Bonjour
AL		SC-P5000Series-FCC1F9	Bonjour
Carl Parties		SC-P5000Series-FCC1F9 (IP)	EPSON TCPIP
AND THE PART OF DEC			
	400.00		
that we want the			
	Mr. to a start and the start a		
	NAME AND A DESCRIPTION OF A DESCRIPTION OF A DESCRIPTION OF A DESCRIPTIONO	Name: Canon PRO-1000 series	
ALL ALL ALL	a same and a second	Location:	
	AND CONTRACTOR	Use: Canon PRO-1000 series	
	Charles and the state of the second sec	atte	
the second se			

9. Close System Preference and resume printing.

At any point if you see a pop-up window telling you 'Upgrade to AirPrint is recommended' click 'Never Upgrade'.

 • • Kenmore P 	RO-300	(D 🔅
	S		
	Upgrade to AirPrint recommended "Kenmore PRO-300" should be upgraded to use AirPrint for future compatibility. Do you want to upgrade		
_	Upgrade		
	Cancel	1751	